GENERAC MOBILE

GMM-150P/FNE [3P - 50HZ - 230V]



Power Rating		
Emergency Standby Power ESP	kVA	165.0
Emergency Standby Power ESP	kW	132.0
Prime power PRP	kVA	150.0
Prime power PRP	kW	120.0
Voltage	V	230
Frequency	Hz	50
Power factor	cos φ	0.8
Phases		3
Fuel		Diesel



Ratings definition (ISO-8528)

ESP - Emergency Standby Power:

It is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 h of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 h of operation shall not exceed 70 % of the ESP. **PRP** - Prime Power:

It is defined as being the maximum power which a generating set is capable of delivering continuously whilst supplying a variable electrical load when operated for an unlimited number of hours per year under the agreed operating conditions with the maintenance intervals and procedures being carried out as prescribed by the manufacturer. The permissible average power output over 24 h of operation shall not exceed 70 % of the prime power.

G2 class load acceptance in accordance with ISO 8528-5:2013 Higher performance classes check upon request.

Gensets are compliant with EC mark which includes the following directives:

• 2006/42/CE Machinery safety.

 2014/30/UE Electromagnetic compatibility. • 2014/35/UE electrical equipment designed for use within certain voltage limits

• 2000/14/EC Sound Power level. Noise emissions outdoor equipment. (amended by 2005/88/EC) - If applicable

• 97/68/EC Emissions of gaseous and particulate pollutants. (amended by 2002/88/EC & 2004/26/EC) -If applicable

• EN 12100, EN 13857, EN 60204

Company with quality certification ISO 9001



Engine specifications		
Engine brand		Perkins
Model		1106A-70TAG2
Operation Speed Nominal	rpm	1500
Engine cooling system		Water
Exhaust emission level		Non Emission Certified
Nr. of cylinder and disposition		6 in line
Displacement	CM ³	7010
Aspiration	Туре	Turbocharged
Speed governor		Mechanical
Gross Engine Power ESP	kWm	153.6
Gross Engine Power PRP	kWm	139.6
Fan Power	kWm	8.6
Fan Air flow	m³/min	222
Total Oil capacity	1	18
Lube oil consumption PRP (max)	% fuel consumption	0.1
Total Coolant capacity	I	20.5
Fuel		Diesel
Specific Fuel consumption ESP	g/kWh	197.6
Specific Fuel consumption 75% PRP	g/kWh	198.8
Starting system		Electric
Electric circuit	V	12



u)

Itorna	tor s	enaci	ficat	ions

Alternator specifications		
Alternator brand		Mecc Alte
Model		ECP34 1L4 C
Winding		Standard
Frequency	Hz	50
Voltage	V	230
Phases		3
Power factor	cos φ	0.8
Stand-by rating 27°C	kVA	165
Continuous Nominal Rating 40°C	kVA	150
Efficiency @ 100% of load	%	93.2
Туре		Brushless
Poles		4
Number of bearing		Single bearing
Voltage tolerance	%	1
Class		Н
IP protection		23

Installation data		
Cooling air	m³/min	261
Exhaust gas flow PRP	m³/min	23.9
Exhaust gas temperature	°C	471
Fuel consumption 75% PRP	l/h	24.77
Fuel consumption 100% PRP	l/h	32.47



Fuel Tank - Options Available:		
To be ordered with equipment (when necessary)		
AUTONOMY		
8PFT Running time 75% PRP	h	14.13
MFT-S Running time 75% PRP	h	13.52
MFT-M Running time 75% PRP	h	26.85



PFT Plastic Fuel Tank	Туре	8
8PFT Fuel tank capacity	I	350
8PFT Fuel tank location		Internal
· ·		
MFT Metal Fuel Tank	Туре	S
MFT-S Fuel tank capacity	I	335
MFT-S Fuel tank location		Internal
MFT Metal Fuel Tank	Туре	М
MFT-M Fuel tank capacity	I	665
MFT-M Fuel tank location		With sub-base
MFT-M EXTRA Height	mm	276
MFT-M EXTRA Weight	Kg	358

www.generacmobile.com





A

Electrical Data		
Battery Voltage	V	12
Genset Voltage	V	230
Frequency	Hz	50
Phases		3
Power Factor	cos φ	0.8
Max current	А	414
Nominal current	А	377
Circuit breaker	А	400

Control panel - Options Available:	
MANUAL REMOTE START PANEL	MRS
AUTOMATIC CONTROL PANEL	ACP
MODULAR PARALLEL PANEL	MPP

MRS - MANUAL REMOTE START PANEL

- Manual and remote start controller
- · Automatic mains failure start function
- 3 phase mains measurements
- 3 phase generator protections
- Running hours
- 50 events, warnings or shutdown alarms with running hours stamp

Power supply by circuit breaker and/or terminal bus bar

ACP - AUTOMATIC CONTROL PANEL

- Auto Mains Failure (AMF) function
- · Gen-set controller for single genset operating in standby or prime power modes
- Full gen-set monitoring and protection
- · Detailed event and performance log with time and date
- Wide range of remote control modules available as option
- Wide range of I/O expansion modules available as option

Power supply by terminal bus bar

MPP - MODULAR PARALLEL PANEL

- Modular parallel panel allows the genset to work in parallel (up to 32 gen-sets)
- · Easy switching between parallel to mains or multiple genset applications
- Full gen-set monitoring and protection
- · Detailed event and performance log with time and date
- · Wide range of communication and connection capabilities available

Power supply by terminal bus bar



CONTROL PANEL - Optional Equipment:

External terminal board	ETB
Differential Protection	ADI







www.generacmobile.com






SOCKETS PANEL - Optional Equipment:

- Sockets panel positioned on the frontal side, separated from control panel cabinets
- High flexibility of sockets kit scope of supply
- Easy and fast power cables connection
- Sockets kit to be define during the order

CANOPY VERSION

- Weatherproof Enclosure made of galvanized sheet metal allows to protect genset from corrosion and aggressive condition
- Soundproofed enclosure tanks to high quality soundproof material and residential silencer, allows to have low noise emission level
- Big large lateral doors allows an easy service and maintenance operation
- Doors equipped with key lockable handles
- Baseframe made of welded steel profile
- Anti-vibration mountings properly sized
- Screwed support legs
- Hole for handling by crane
- · Moving and rotating parts protection against accidental contact
- · Grounding point to connect all metal parts to ground
- · Robust Lifting bridge, with single lifting point positioned on the roof





0.0

Н

W

Dimensional data Canopy Version

Length	(L) mm	3090
Width	(W) mm	1100
Height	(H) mm	1852

Weight	Kg	1917

Noise Level Canopy Version

©2023 | www.generacmobile.com

Guaranteed noise level (LWA)	dB(A)	97
Noise pressure level @ 1 m	dB(A)	79
Noise pressure level @ 7 m	dB(A)	68

OPTIONAL FEATURES	
To be ordered with equipment (when necessary)	:
Pre-Heating System	PHS
Air Shut-Off Valve	ASV
Electronic Engine Governor	EEG
Heavy-Duty Air Filter	HDF
Water Separator Filter	WSP
Exhaust Spark Arrestor	ESA









-

_